

ROLAND SH-01A **ULTIMATE PATCHES**

Remember to back up your patches before loading in the Ultimate Patches for SH-01A.

Backup your patches

1. While holding down the SH-01A "MENU" button, turn on the power of your SH-01A.
2. Connect your computer to the SH-01A USB port via a USB cable. The "SH-01A" drive will appear in your hard drive list.
3. Double click (open) that "SH-01A" drive. You'll now see 2 folders: "PATCH" and "PATTERN" located in the "BACKUP" folder of the "SH-01A" drive.
4. Copy that BACKUP folder to your computer.
5. After copying is completed, eject the USB drive and then disconnect the USB cable.

How to load our patches into your SH-01A

1. Connect the SH-01A to your computer via USB.
2. Turn on the SH-01A while holding how the "MENU" key on the SH-01A.
3. A "SH-01A" drive will show up on your computer.
4. Drag the "PATCH" folder (which is in the SH-01A Ultimate Patches BACKUP folder) into the RESTORE folder on the SH-01A drive on your computer.
5. Once the contents are done copying, press the MENU button on your SH-01A. Wait a few seconds (until the lights stop scrolling on your SH-01A), then restart the SH-01A.
6. The patches will now be installed.

Next page: how to create your own "mix and match" custom set of patches.



How to create your own “mix and match” set of patches:

Do you want to choose a few patches and create your own collection to load into your SH-01A? No problem.

First, this is how the patch numbering works in the SH-01A. In the PATCH folder which is in the BACKUP folder, you’ll find all the patch files, named SH01A_PATCHx_zz.prm, where x is the bank number, and zz is the patch number in that bank.

For example:

SH01A_PATCH8_08.prm
is bank 8, patch 8

SH01A_PATCH1_01.prm
is bank 1, patch 1

etc

So, you can create a blank folder on your computer called BACKUP and put another folder inside that that called PATCH, then copy any patches (eg SH01A_PATCH8_08.prm etc) that you want, into that PATCH folder. That BACKUP folder can be loaded into your SH-01A or backed up from your SH-01A as instructed on page one of this manual.

In addition, you can renumber any of those patch filenames so they load into the SH-01A patch slot you prefer. So for example, if you wanted to make Patch 3 Bank 1 load into Patch 3 Bank 5, you would do this:

SH01A_PATCH1_03.prm

rename to

SH01A_PATCH5_03.prm

Should you have any difficulties feel free to contact support@ultimatepatches.com. We typically reply within 24 hours. We want you to get up and running to enjoy your patches! :)

